



Anti-theft main engine and common vehicle distribution wire function contrast form

Vehicle Wire	Mainframe Wire Color	HONDA Wire Color	SANYANG Wire Color	YAMAHA Wire Color	SUZUKI Wire Color
12v(+)	Red	Red	Red	Red	Red
12v(-)	Black	Green	Green	Black	Black/White
Key on+12v	Orange	Black	Black	Brown	Orange
Start Wire	Blue	Yellow/Red	Yellow/Red	Blue/White	Black/White
Ignition off (Up)	Pink	Black and White(Up)	Black and White(Up)	Black and White(Up)	
Ignition off (Dowm)	Gray	Black and White (Down)	Black and White (Down)	Black and White (Down)	(Remark1)
Direction Light	Yellow	Lighte Blue	Light Blue	Deep Brown	Black
Direction Light	Yellow	Orange	Orange	Deep Green	Green

Remork(1): Low voltage auto tester is suggested to test which terminal is for turning off the engine.